



















More information on the website  
[radwag.com/en/info,w1,TUT](http://radwag.com/en/info,w1,TUT)

# WPY 3/6.F1.R.PGC Scale



The drawings, photos and graphics used are for illustrative purposes only.

## Functions

-  Dosing
-  Labelling
-  Plus/Minus Control
-  Percent Weighing
-  Totalizing
-  Parts counting
-  Peak hold
-  Formulation
-  Newton unit measurement
-  Statistics
-  Checkweighing
-  IR sensors
-  Animal weighing
-  Differential weighing
-  Packaged Goods Control
-  ALIBI Memory

## Datasheet

Metrological parameters	
Maximum capacity [Max]	3 / 6 kg
Minimum load	20 / 40 g
Readability [d]	1 / 2 g
Tare range	-6 kg
OIML Class	III

Physical parameters	
Display	5,7" Resistiv-Farb-Touchscreen
Weighing pan dimensions	300×300 mm
Packaging dimensions	570×390×170 mm
Communication interface	
Communication interface	2×RS232, 2×USB-A, Ethernet, 4 IN / 4 OUT (digital), Wi-Fi
Electrical parameters	
Power supply	100 – 240 V AC 50/60 Hz
Environmental conditions	
Operating temperature	-10 ÷ +40 °C
Relative humidity	10% ÷ 85% RH no condensation

\* Wi-Fi® is a registered trademark of Wi-Fi® Alliance.



## Accessories

Transponder card readers  
 RS 232 cables (scale - printer)  
 Barcode scanners  
 Cigarette lighter receptacle power supply cables  
 RS 232, RS 485 cables  
 USB Hubs  
 Label Printers  
 Displays

IN/OUT Cables  
 Keypad, external switches  
 Stands, wall mounting kits and mounting brackets  
 Receipt Printer  
 F1 Mass Standard - knob weights without adjustment chamber, set  
 AP2-1 Current Loop Unit  
 Additional Weighing platforms Module  
 RS 232 – USB Converter

## Software

E2R System  
 Audit Trail Reader  
 Label Editor R02  
 R-LAB  
 RADWAG Development Studio

RAD-KEY  
 LabVIEW Driver  
 RADWAG Remote Desktop  
 Scales Editor 2.1  
 R.Barcode