



More information on the website  
radwag.com/en/info,w1,Y77

# CY10.150/300.C3.K.M3 Multifunctional Scale



The drawings, photos and graphics used are for illustrative purposes only.

## Functions



Dosing



Percent Weighing



Parts counting



Peak hold



Formulation



IR sensors



Animal weighing



Statistical Quality Control



Wi-Fi

## Datasheet

Metrological parameters	
Maximum capacity [Max]	150/300 kg
Minimum load	1000 g
Readability [d]	50/100 g
Verification unit [e]	50 g
Tare range	-300 kg
Stabilization time	3 s
Adjustment	external

Metrological parameters	
OIML Class	III
Physical parameters	
Leveling system	manual
Display	10" graphic colour touchscreen
Weighing pan dimensions	500×700 mm
Packaging dimensions	850×800×270 mm
Net weight	22.7 kg
Gross weight	26.5 kg
Cable length	2.5 m
Multiple range	YES
Construction	
Protection class	IP 43
Housing	steel + ABS
Communication interface	
Communication interface	2×USB-A, USB-C, HDMI, Ethernet, Wi-Fi, Hotspot
Electrical parameters	
Power supply	12÷15V DC
Power consumption	1A
Environmental conditions	
Operating temperature	-10 ÷ +40 °C
Storage temperature	-25 ÷ +70 °C
Features of use	
Max number of platforms	max.2

**Stabilization time** depends on the ambient conditions and the dynamics of weighing pan loading; specified for FAST profile.

\* Wi-Fi® is a registered trademark of Wi-Fi® Alliance.



Extra payment for verification



## Accessories

MediaBox  
 Mild steel powder coated weighing platforms  
 RFID Tags  
 Power Adapters  
 Additional Weighing platforms Module  
 Mild steel powder coated weighing platforms  
 Additional modules  
 Platforms in plastic casing

Protective cover for balances  
 Barcode scanners  
 Label Printers  
 RS 232, RS 485 cables  
 Stands, wall mounting kits and mounting brackets  
 Fingerprint Reader  
 RS 232 – USB Converter  
 Receipt Printer

## Software

• E2R Weighing [WX-010-0099]

• E2R Weighing Records [WX-010-0038]

- RAD Key [WX-010-0005]
- RADWAG Remote Desktop [WX-010-0107]

- Label Editor R02 [WX-010-0094]
- Scale Editor 2.1 [WX-010-0173]

## Device dimensions

